arXiv:1302.4396v3 [math.FA] 2 Apr 2013

On the Determination of a Function from an Elliptical Radon Transform

Sunghwan Moon

Department of Mathematics,Texas A&M University,College Station, Tx77843-3368

Abstract

In recent years, Radon type transforms that integrate functions over various sets of ellipses/ellipsoids have been considered in SAR, ultrasound reflection tomography, and radio tomography. In this paper, we consider the transform that integrates a given function in $\mathbb{R}^n$ over a set of solid ellipsoids of rotation with a fixed eccentricity and foci restricted to a hyperplane. Inversion formulas are obtained for appropriate classes of functions that are even with respect to the hyperplane. Stability estimates, range description, and local uniqueness results are also provided.

Keywords: Elliptical, Radon, Radio, Tomography

---

1. Introduction

Radon type transforms that integrate functions over various sets of ellipses/ellipsoids have been arising in the recent decade, due to studies in synthetic aperture radar (SAR) [1, 4, 8, 9], ultrasound reflection tomography [7, 2], and radio tomography [16, 15, 17]. In particular, radio tomography is a new imaging method, which uses a wireless network of radio transmitters and receivers to image the distribution of attenuation within the network. The usage of radio frequencies brings in significant non-line-of-sight propagation, since waves propagate along many paths from a transmitter to a receiver. Given a transmitter and a receiver, wave paths observed for a given duration are all contained in an ellipsoid with foci at these two devices. It was thus suggested in [16, 17, 15] to approximate the obtained signal by the volume integral of the attenuation over this ellipsoid, which is the model we study in this article.

Due to these applications, there have been several papers devoted to such "elliptical Radon transform." The family of ellipses with one focus fixed at the origin and the other one moving along a given line was considered in [9]. In the same paper, the family of ellipses with a fixed focal distance was also studied. The authors of [2, 7] dealt with the case of circular acquisition, when the two foci of ellipses with a given focal distance are located on a given circle. A family of ellipses with two moving foci was also handled in [4].

In all these works, however, the ellipses have varying eccentricity. Also, their data were the line integrals of the function over ellipses rather than area integrals. The radio tomography application makes it interesting to consider integrals over solid ellipsoids. In this article, we consider the volume integrals of an unknown attenuation function over the family of ellipsoids of rotation in $\mathbb{R}^n$ with a fixed eccentricity and two foci located in a given hyperplane. We thus reserve the name **elliptical Radon transform** $R_E f$ for the volume integral of a function f over this family of ellipsoids.

The volume integral of a function $f(x)$ over an ellipsoid of the described type is equal to zero if the function is odd with respect to the chosen hyperplane. If the hyperplane is given by $x_n = 0$, we thus assume the function $f(x) : \mathbb{R}^n \to \mathbb{R}$ to be even w.r.t. x_n: $f(x', x_n) = f(x', -x_n)$ where $x = (x', x_n) \in \mathbb{R}^{n-1} \times \mathbb{R}$.

Given a Radon type transform, one is usually interested, among others, in the following questions: uniqueness of reconstruction, inversion formulas and algorithms, stability estimates, and range description [11, 12]. These are the issues we address below.

The problem is stated precisely in section 2. Various inversion formulas are presented in sections 3 and 4. Sobolev estimates and range description are handled in section 5. Section 6 is devoted uniqueness for a local data problem.

2. Formulation of the problem

We consider all solid ellipsoids of rotation in $\mathbb{R}^n$ with a fixed eccentricity $1/\lambda$, where $\lambda > 1$ and foci located in the hyperplane $x_n = 0$. We will identify this hyperplane with $\mathbb{R}^{n-1}$. The set of such ellipsoids depends upon $2n-2$ parameters, which is $n-2$ too many. To reduce the overdeterminacy, we require that the focal axis is parallel to a given line, for instance, the x_1 coordinate axis.

Let $u \in \mathbb{R}^{n-1}$ be the center of such an ellipsoid and let $t > 0$ be the half of the focal distance. We denote this ellipsoid by $E_{u,t}$. Then, the foci are

$$c_1 = (u_1 + t, u_2, \cdots, u_{n-1}, 0) \text{ and } c_2 = (u_1 - t, u_2, \cdots, u_{n-1}, 0)$$

and the points $x \in E_{u,t}$ are described as follows:

$$\frac{(x_1 - u_1)^2}{\lambda^2} + \frac{(x_2 - u_2)^2}{\lambda^2 - 1} + \cdots + \frac{x_n^2}{\lambda^2 - 1} \le t^2.$$

To shorten the formulas, we are going to use the following notation:

$$\nu := \sqrt{\lambda^2 - 1}.$$

The elliptical Radon transform R_E maps a function $f(x)$ into its integrals over the solid ellipsoids $E_{u,t}$ for all $u \in \mathbb{R}^{n-1}$ and $t > 0$:

$$R_E f(u, t) = \int\limits_{E_{u,t}} f(x) dx.$$

Our goals are to reconstruct f from $R_E f$ and to study properties of this transform.

3. Inversion of the elliptical Radon Transform

In this section, we assume $f \in C_c^\infty(\mathbb{R}^n)$. Let χ_S denote the characteristic function of a set $S \subset \mathbb{R}^n$:

$$\chi_S(x) = \begin{cases} 1, & \text{if } x \in S, \\ 0, & \text{otherwise} \end{cases}.$$

Then the elliptical Radon transform can be written as

$$\begin{aligned} R_E f(u,t) &= \int\limits_{\mathbb{R}^n} \chi_{E_{u,t}} f(x) dx = C(\lambda) \int\limits_{\mathbb{R}^n} \chi_{|x|<t} f(\lambda x_1 + u_1, \nu \tilde{x} + \tilde{u}, \nu x_n) dx \\ &= C(\lambda) \int\limits_0^t r^{n-1} \int\limits_{S^{n-1}} f(\lambda r y_1 + u_1, \nu r \tilde{y} + \tilde{u}, r \nu y_n) d\sigma(y) dr, \end{aligned} \tag{1}$$

where $u = (u_1, \tilde{u}) \in \mathbb{R}^{n-1}$, $x = (x_1, \tilde{x}, x_n) \in \mathbb{R}^n$, $C(\lambda) = \lambda \nu^{n-1}$ is the Jacobian factor, and $\sigma(y)$ is the surface measure on S^{n-1}.

Formula (1) can be simplified by differentiation with respect to t and division by t^{n-1} which yield

$$\begin{aligned} \frac{1}{t^{n-1}} \frac{\partial}{\partial t} R_E f(u,t) &= C(\lambda) \int\limits_{|y|=1} f(\lambda t y_1 + u_1, \nu t \tilde{y} + \tilde{u}, t \nu y_n) d\sigma(y) \\ &= C(\lambda) \int\limits_{|y'| \le 1} f(u + (t\lambda y_1, t\nu \tilde{y}), t\nu \sqrt{1 - |y'|^2}) \frac{dy'}{\sqrt{1 - |y'|^2}}, \end{aligned} \tag{2}$$

where $y' = (y_1, \tilde{y}) \in \mathbb{R}^{n-1}$.

It is easy to check that R_E is invariant under the shift with respect to the first $n-1$ variables. That is, if $f_a(x) := f(x' + a, x_n)$ for $x = (x', x_n) \in \mathbb{R}^n$ and $a \in \mathbb{R}^{n-1}$, we have

$$(R_E f_a)(u,t) = (R_E f)(u + a, t).$$

Thus, application of the $(n-1)$-dimensional Fourier Transform with respect to the center u seems reasonable. Doing this and changing the variable $y' \in \mathbb{R}^{n-1}$ to the polar coordinates $(\theta, s) \in S^{n-1} \times [0, \infty)$, we get

$$\frac{1}{t^{n-1}} \frac{\partial}{\partial t} \widehat{R_E f}(\xi', t) = 2C(\lambda) \int\limits_0^1 \frac{s^{n-2}}{\sqrt{1-s^2}} \hat{f}(\xi', t\nu\sqrt{1-s^2}) \int\limits_{S^{n-2}} e^{its(\lambda\theta_1, \nu\tilde{\theta}) \cdot \xi'} d\theta ds,$$

where $\widehat{R_E f}$ and $\hat{f}$ are Fourier Transforms of $R_E f$ and f with respect to the first $n-1$ coordinates x' of x and u of (u,t), respectively, and $\theta = (\theta_1, \tilde{\theta}) \in S^{n-2}$.

To compute the inner integral, we use the known identity [3, 6]

$$\int\limits_{S^{n-1}} e^{i\xi\cdot\theta}d\theta = (2\pi)^{n/2}|\xi|^{(2-n)/2}J_{(n-2)/2}(|\xi|).$$

We thus get

$$\frac{1}{t^{n-1}}\frac{\partial}{\partial t}\widehat{R_E f}\left(\frac{\xi_1}{\lambda},\frac{\tilde{\xi}}{\nu},t\right) = \omega_n\int\limits_0^1 \frac{s^{n-2}}{\sqrt{1-s^2}}\hat{f}\left(\frac{\xi_1}{\lambda},\frac{\tilde{\xi}}{\nu},t\nu\sqrt{1-s^2}\right)(ts|\xi'|)^{(3-n)/2}J_{(n-3)/2}(ts|\xi'|)ds,$$

where $\omega_n = 2(2\pi)^{(n-1)/2}C(\lambda)$.

We define the back projection operator R_E^* for $g(u,t)\in C_c^\infty(\mathbb{R}^{n-1}\times\mathbb{R}_+)$ as

$$R_E^*g(x) = \int\limits_{\mathbb{R}^{n-1}} g\left(u,\sqrt{\frac{|u_1-x_1|^2}{\lambda^2}+\frac{|\tilde{u}-\tilde{x}|^2}{\nu^2}+\frac{x_n^2}{\nu^2}}\right)du. \tag{3}$$

In fact, $R_E^*g(x)$ is the dual transform not to $R_Ef(u,t)$, but rather to $\frac{\partial}{\partial t}R_Ef(u,t)$, i.e.,

$$\int\limits_0^\infty\int\limits_{\mathbb{R}^{n-1}}\frac{\partial}{\partial t}R_Ef(u,t)g(u,t)dudt = \int\limits_{\mathbb{R}^n} f(x)R_E^*g(x)dx.$$

We thus get analogue of the Fourier slice formula.

Theorem 1. *For a function $f\in C_c^\infty(\mathbb{R}^n)$ which is even with respect to x_n the following formula holds:*

$$\hat{f}(\xi) = \frac{|(\lambda\xi_1,\nu\tilde{\xi},\nu\xi_n)|^{n-2}|\xi_n|}{2C(\lambda)^2}\mathcal{F}\left(R_E^*\frac{1}{t^{n-1}}\frac{\partial}{\partial t}R_Ef\right)(\xi), \tag{4}$$

where $\mathcal{F}f$ is the n-dimensional Fourier transform of f.

Proof. Let us denote the radial Fourier transform by $H_nf(\rho)$, i.e.,

$$H_nf(\rho) := \rho^{1-n/2}\int\limits_0^\infty r^{n/2}J_{(n-2)/2}(r\rho)f(r)dr.$$

Taking this transform of $\frac{1}{t^{n-1}}\frac{\partial}{\partial t}\widehat{R_E f}$ as a function of t, we have for $\xi=(\xi_1,\tilde{\xi})=\xi'\in\mathbb{R}^{n-1}$,

$$\begin{aligned}&H_n\left(\frac{1}{t^{n-1}}\frac{\partial}{\partial t}\widehat{R_E f}\right)\left(\frac{\xi_1}{\lambda},\frac{\tilde{\xi}}{\nu},\rho\right)\\ &= \omega_n\rho^{1-n/2}\int\limits_0^\infty\int\limits_0^1 t^{\frac{3}{2}}J_{\frac{n-2}{2}}(t\rho)(s|\xi'|)^{\frac{3-n}{2}}J_{\frac{n-3}{2}}(ts|\xi'|)\hat{f}\left(\frac{\xi_1}{\lambda},\frac{\tilde{\xi}}{\nu},t\nu\sqrt{1-s^2}\right)\frac{s^{n-2}dsdt}{\sqrt{1-s^2}}.\end{aligned} \tag{5}$$

It is known in [5, p. 59 (18) vol.2 or for $n = 2$, p.55 (35) vol.1] that for $a > 0, \beta > 0$, and, $\mu > \nu > -1$,

$$\begin{aligned}&\int_0^\infty x^{\nu+1/2}(x^2+\beta^2)^{-1/2\mu}J_\mu(a(x^2+\beta^2)^{1/2})J_\nu(xy)(xy)^{1/2}dx\\ &=\begin{cases} a^{-\mu}y^{\nu+1/2}\beta^{-\mu+\nu+1}(a^2-y^2)^{1/2\mu-1/2\nu-1/2}J_{\mu-\nu-1}(\beta(a^2-y^2)^{1/2}) & \text{if } 0<y<a,\\ 0 & \text{if } a<y<\infty.\end{cases}\end{aligned}$$

To use the above identity, we make the change of variables $(s, t) \to (x, \beta)$, where $t = \sqrt{x^2+\beta^2}$ and $s = x/\sqrt{x^2+\beta^2}$ in (5), which gives

$$\begin{aligned}&H_n\left(\frac{1}{t^{n-1}}\frac{\partial}{\partial t}\widehat{R_E f}\right)\left(\frac{\xi_1}{\lambda},\frac{\tilde{\xi}}{\nu},\rho\right)\\ &=\omega_n\rho^{\frac{2-n}{2}}|\xi'|^{3-n}\int_0^\infty\int_0^\infty |x|J_{\frac{n-2}{2}}(\rho(x^2+\beta^2)^{\frac{1}{2}})(x^2+\beta^2)^{-\frac{n-2}{4}}J_{\frac{n-3}{2}}(x|\xi'|)\hat{f}\left(\frac{\xi_1}{\lambda},\frac{\tilde{\xi}}{\nu},t\nu\sqrt{1-s^2}\right)dxd\beta\\ &=\begin{cases} C(\lambda)\dfrac{2^{n/2+1}\pi^{n/2}\rho^{2-n}}{\sqrt{\rho^2-|\xi'|^2}}\displaystyle\int_0^\infty \hat{f}\left(\frac{\xi_1}{\lambda},\frac{\tilde{\xi}}{\nu},\beta\nu\right)\cos(\sqrt{\rho^2-|\xi'|^2}\beta)d\beta & \text{if } |\xi'|<\rho,\\ 0 & \text{otherwise.}\end{cases}\end{aligned} \tag{6}$$

Substituting $\rho = |\xi|$ yields

$$H_n\left(\frac{1}{t^{n-1}}\frac{\partial}{\partial t}\widehat{R_E f}\right)\left(\frac{\xi_1}{\lambda},\frac{\tilde{\xi}}{\nu},|\xi|\right)=C(\lambda)\frac{2^{n/2+1}\pi^{n/2}|\xi|^{2-n}}{|\xi_n|}\int_0^\infty \hat{f}\left(\frac{\xi_1}{\lambda},\frac{\tilde{\xi}}{\nu},\beta\nu\right)\cos(\xi_n\beta)d\beta.$$

Since f is even in x_n, the last integral is Fourier transform of f with respect to $x - n$, so we get

$$H_n\left(\frac{1}{t^{n-1}}\frac{\partial}{\partial t}\widehat{R_E f}\right)\left(\frac{\xi_1}{\lambda},\frac{\tilde{\xi}}{\nu},|\xi|\right)=\frac{2^{n/2+1}\pi^{n/2}|\xi|^{2-n}}{|\xi_n|}\lambda\nu^{n-2}\hat{f}\left(\frac{\xi_1}{\lambda},\frac{\tilde{\xi}}{\nu},\frac{\xi_n}{\nu}\right). \tag{7}$$

Taking Fourier transform of $R_E^* g$ with respect to x yields

$$\begin{aligned}
&\widehat{R_E^* g}\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}, \frac{\xi_n}{\nu}\right) = \int\limits_{\mathbb{R}^n} e^{-ix\cdot\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}, \frac{\xi_n}{\nu}\right)} R_E^* g(x)dx \\
&= \int\limits_{\mathbb{R}^n} e^{-ix\cdot\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}, \frac{\xi_n}{\nu}\right)} \int\limits_{\mathbb{R}^{n-1}} g\left(u, \sqrt{\frac{|u_1 - x_1|^2}{\lambda^2} + \frac{|\tilde{u} - \tilde{x}|^2}{\nu^2} + \frac{x_n^2}{\nu^2}}\right) dudx \\
&= \int\limits_{\mathbb{R}^{n-1}} e^{-iu\cdot\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}\right)} \int\limits_{\mathbb{R}^n} e^{-i(x'-u,x_n)\cdot\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}, \frac{\xi_n}{\nu}\right)} g\left(u, \sqrt{\frac{|u_1 - x_1|^2}{\lambda^2} + \frac{|\tilde{u} - \tilde{x}|^2}{\nu^2} + \frac{x_n^2}{\nu^2}}\right) dxdu \\
&= C(\lambda) \int\limits_{\mathbb{R}^{n-1}} e^{-iu\cdot\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}\right)} \int\limits_{\mathbb{R}^n} e^{-ix\cdot\xi} g(u, |x|)dxdu \\
&= (2\pi)^{-n/2} C(\lambda) \int\limits_{\mathbb{R}^{n-1}} e^{-iu\cdot\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}\right)} (H_n g(u, \cdot))(|\xi|)du \\
&= (2\pi)^{-n/2} C(\lambda) H_n \widehat{g}\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}, |\xi|\right).
\end{aligned} \tag{8}$$

where $x = (x', x_n) = (x_1, \tilde{x}, x_n) \in \mathbb{R}^n$, $u = (u_1, \tilde{x}) \in \mathbb{R}^{n-1}$ and $\xi = (\xi', \xi_n) = (\xi_1, \tilde{\xi}, \xi_n) \in \mathbb{R}^n$. Combining (7) and (8), we get (4). ☐

Corollary 2. *Theorem 1 leads naturally to a Fourier type inversion formula for even function, if one supplements* (4) *with the inverse Fourier transform.*

Remark 3. *Since* $(i\xi)^\alpha \hat{f}(\xi) = \widehat{\frac{\partial^\alpha}{\partial x^\alpha} f}(\xi)$, *we get for any* $\alpha, \beta > 0$,

$$\begin{aligned}
\hat{f}(\xi) = (-1)^\alpha (-i\,\mathrm{sgn}(\xi_n))^\beta \quad & \frac{|(\lambda\xi_1, \nu\tilde{\xi}, \nu\xi_n)|^{n-2-2\alpha} |\xi_n|^{1-\beta}}{2C(\lambda)^2} \\
& \times \mathcal{F}\left(R_E^*\left(\left(\frac{x_n}{\nu^2 t}\right)^\beta \frac{\partial^{2\alpha+\beta}}{\partial t^{2\alpha+\beta}}\left(t^{1-n}\frac{\partial}{\partial t} R_E f\right)\right)\right)(\xi).
\end{aligned}$$

One can also obtain a useful relation with convolution.

Proposition 4. *Let* $\phi \in C_c^\infty(\mathbb{R}^{n-1} \times [0, \infty))$, $\psi = R^*\phi$, $f \in C_c^\infty(\mathbb{R}^n)$ *and* $g = \frac{1}{t^{n-1}} \frac{\partial}{\partial t} R_E f$. *Then we have*

$$g * \phi = \frac{(2\pi)^{n/2}}{C(\lambda) t^{n-1}} \frac{\partial}{\partial t} R_E (f * \psi),$$

where

$$g * \phi(u, t) = \int\limits_0^\infty \int\limits_{\mathbb{R}^{n-1}} g(u - u', t - t')\phi(u', t')du'dt'.$$

Proof. Note that since H_n is also a radial Fourier transform, we get $H_n(f * g) = H_n f H_n g$ and $H_n H_n f = f$. Taking Fourier transform on $g * \phi$ with respect to u and H_n with respect to t, we get

$$\begin{aligned} H_n\widehat{g * \phi}\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}, |\xi|\right) &= H_n\hat{g}\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}, |\xi|\right) H_n\hat{\phi}\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}, |\xi|\right) \\ &= \frac{(2\pi)^{n/2}}{C(\lambda)} H_n\hat{g}\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}, |\xi|\right) \hat{\psi}\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}, \frac{\xi_n}{\nu}\right). \end{aligned}$$

In last line we used equation (8). Equation (7) implies

$$\begin{aligned} H_n\widehat{g * \phi}\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}, |\xi|\right) &= \frac{2^{n/2+1}\pi^n |\xi|^{2-n}\nu^{n-2}\lambda}{C(\lambda)|\xi_n|} \hat{f}\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}, \frac{\xi_n}{\nu}\right) \hat{\psi}\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}, \frac{\xi_n}{\nu}\right) \\ &= \frac{2^{n/2+1}\pi^n |\xi|^{2-n}\nu^{n-2}\lambda}{C(\lambda)|\xi_n|} \widehat{f * \phi}\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}, \frac{\xi_n}{\nu}\right) \\ &= \frac{(2\pi)^{n/2}}{C(\lambda)} H_n\left(\frac{1}{t^{n-1}}\frac{\partial}{\partial t} R_E\widehat{f * \phi}\right)\left(\frac{\xi_1}{\lambda}, \frac{\tilde{\xi}}{\nu}, |\xi|\right), \end{aligned}$$

which proves our assertion. □

4. Another Inversion

In this section, we provide a different inversion formula for the elliptical Radon transform. To get it, we start from formula (2). Let us define

$$\begin{aligned} G(u, w) &:= \int_0^\infty \frac{\partial}{\partial t} R_E f(u, t) e^{iwt^2} dt \\ &= C(\lambda) \int_0^\infty t^{n-1} \int_{|y|=1} f(\lambda t y_1 + u_1, \nu t \tilde{y} + \tilde{u}, t\nu y_n) e^{iwt^2} d\sigma(y) dt \\ &= C(\lambda) \int_{\mathbb{R}^{n-1}} f(\lambda y_1 + u_1, \nu \tilde{y} + \tilde{u}, \nu y_n) e^{iw|y|^2} dy, \end{aligned}$$

where in the last equality we switched from polar to Cartesian coordinates.

Theorem 5. *Let $f \in C_c^\infty(\mathbb{R}^n)$ with $f(x', x_n) = f(x', -x_n)$. Then we have*

$$f(x) = \frac{x_n}{(2\pi)^n C(\lambda)^2} \int_{\mathbb{R}^n} e^{-i\frac{|\alpha|^2}{4\gamma}} e^{i\alpha\cdot\left(\frac{x_1}{\lambda}, \frac{\tilde{x}}{\nu}\right)} e^{-i\gamma\left(\frac{x_1^2}{\lambda^2} + \frac{|\tilde{x}|^2}{\nu^2} + \frac{x_n^2}{\nu^2}\right)} G\left(\frac{\alpha_1\lambda}{2\gamma}, \frac{\alpha'\nu}{2\gamma}, \gamma\right) d\alpha d\gamma,$$

for $x_n > 0$, where $C(\lambda) = \lambda\nu^{n-1}$, as before.

Proof. Making the change of variable $x_1 = \lambda t y_1 + u_1, \tilde{x} = \nu t \tilde{y} + \tilde{u}, x_n = t\nu y_n$, we get

$$\begin{aligned} G(u,w) &= \int\limits_{\mathbb{R}^n} f(x) e^{iw\left(\frac{(x_1-u)^2}{\lambda^2} + \frac{|\tilde{x}-\tilde{u}|^2}{\nu^2} + \frac{x_n^2}{\nu^2}\right)} dx \\ &= e^{iw\frac{u^2}{\lambda^2}} e^{iw\frac{|\tilde{u}|^2}{\nu^2}} \int\limits_{\mathbb{R}^n} f(x) e^{iw\left(\frac{x_1^2}{\lambda^2} + \frac{|\tilde{x}|^2}{\nu^2} + \frac{x_n^2}{\nu^2}\right)} e^{-2iwu_1\frac{x_1}{\lambda^2}} e^{-2iw\frac{\tilde{u}\cdot\tilde{x}}{\nu^2}} dx, \end{aligned}$$

where $x = (x_1, \tilde{x}, x_n)$ and $u = (u_1, \tilde{u}) \in \mathbb{R}^{n-1}$. Next, make the change of variables

$$x_{1,temp} = \frac{x_1}{\lambda}, \qquad \tilde{x}_{temp} = \frac{\tilde{x}}{\nu}, \qquad \text{and} \qquad r = \frac{x^2}{\lambda^2} + \frac{|\tilde{x}|^2}{\nu^2} + \frac{x_n^2}{\nu^2},$$

so that

$$x_1 = x_{1,temp}\lambda, \qquad \tilde{x} = \tilde{x}_{temp}\nu, \qquad \text{and} \qquad x_n = \nu\sqrt{r - x_{1,temp}^2 - |\tilde{x}_{temp}|^2}.$$

The Jacobian of this transformation is

$$\begin{aligned} J &= \begin{vmatrix} \lambda & 0 & \cdots & 0 \\ 0 & \nu & \cdots & 0 \\ \vdots & \vdots & \ddots & \vdots \\ \frac{-x_{1,temp}\nu}{2\sqrt{r - x_{1,temp}^2 - \tilde{x}_{temp}^2}} & \frac{-\tilde{x}_{temp}\nu}{2\sqrt{r - x_{1,temp}^2 - |\tilde{x}_{temp}|^2}} & \cdots & \frac{\nu}{2\sqrt{r - x_{1,temp}^2 - |\tilde{x}_{temp}|^2}} \end{vmatrix} \\ &= \frac{C(\lambda)}{2\sqrt{r - x_{1,temp}^2 - |\tilde{x}_{temp}|^2}} \end{aligned}$$

so that

$$dx = \frac{C(\lambda)}{2\sqrt{r - x_{1,temp}^2 - |\tilde{x}_{temp}|^2}} dx_1 d\tilde{x} dr.$$

Let the function $k(x, \tilde{x}, r)$ be defined by

$$k(x, \tilde{x}, r) = \begin{cases} \dfrac{f(\lambda x_1, \nu\tilde{x}, \nu\sqrt{r - x_1^2 - |\tilde{x}|^2})}{2\sqrt{r - x_1^2 - |\tilde{x}|^2}} & 0 < |x_1|^2 + |\tilde{x}|^2 < r, \\ 0 & \text{otherwise.} \end{cases}$$

Since f is even in x_n, it is sufficient to consider the positive root of $\sqrt{r - x_1^2 - |\tilde{x}|^2}$. Then we can rewrite $G(u,w)$ as

$$\begin{aligned} G(u,w) &= C(\lambda) e^{iw\frac{u_1^2}{\lambda^2}} e^{iw\frac{|\tilde{u}|^2}{\nu^2}} \int_{\mathbb{R}^n} k(x_1, \tilde{x}, r) e^{iwr} e^{-2i\frac{wx_1 u}{\lambda}} e^{-2i\frac{w\tilde{x}\cdot\tilde{u}}{\nu}} dx_1 d\tilde{x} dr \\ &= C(\lambda) e^{iw\frac{u_1^2}{\lambda^2}} e^{iw\frac{|\tilde{u}|^2}{\nu^2}} K\left(2\frac{wu_1}{\lambda}, 2\frac{w\tilde{u}}{\nu}, -w\right), \end{aligned}$$

where for $\alpha = (\alpha_1, \alpha') \in \mathbb{R} \times \mathbb{R}^{n-2}$,

$$\begin{aligned} K(\alpha, \gamma) &= \int_{\mathbb{R}^n} e^{-i\alpha\cdot(x_1,\tilde{x})} e^{-i\gamma r} k(x_1, \tilde{x}, r) dx_1 d\tilde{x} dr \\ &= \frac{1}{C(\lambda)} e^{i\frac{|\alpha|^2}{4\gamma}} G\left(\frac{-\alpha_1\lambda}{2\gamma}, \frac{-\alpha'\nu}{2\gamma}, -\gamma\right). \end{aligned}$$

Since $k(x, \tilde{x}, r)$ is

$$\frac{1}{(2\pi)^n} \int_{\mathbb{R}^n} e^{i\alpha_1 x_1} e^{i\alpha'\cdot\tilde{x}} e^{i\gamma r} K(\alpha, \gamma) d\alpha d\gamma,$$

we get for $x_n > 0$,

$$\begin{aligned} f(x) &= \frac{x_n}{C(\lambda)} k\left(\frac{x_1}{\lambda}, \frac{\tilde{x}}{\nu}, \frac{x_1^2}{\lambda^2} + \frac{|\tilde{x}|^2}{\nu^2} + \frac{x_n^2}{\nu^2}\right) \\ &= \frac{x_n}{(2\pi)^n C(\lambda)} \int_{\mathbb{R}^n} e^{i\alpha_1\frac{x_1}{\lambda}} e^{i\alpha'\cdot\frac{\tilde{x}}{\nu}} e^{i\gamma\left(\frac{x_1^2}{\lambda^2}+\frac{|\tilde{x}|^2}{\nu^2}+\frac{x_n^2}{\nu^2}\right)} K(\alpha, \gamma) d\alpha d\gamma \qquad (9) \\ &= \frac{x_n}{(2\pi)^n C(\lambda)^2} \int_{\mathbb{R}^n} e^{-i\frac{|\alpha|^2}{4\gamma}} e^{i\alpha\cdot\left(\frac{x_1}{\lambda},\frac{\tilde{x}}{\nu}\right)} e^{-i\gamma\left(\frac{x_1^2}{\lambda^2}+\frac{|\tilde{x}|^2}{\nu^2}+\frac{x_n^2}{\nu^2}\right)} G\left(\frac{\alpha_1\lambda}{2\gamma}, \frac{\alpha'\nu}{2\gamma}, \gamma\right) d\alpha d\gamma. \end{aligned}$$

□

5. A Sobolev Estimate and Range description

In this section we obtain a Sobolev estimate for the elliptical Radon transform and describe its range. Let $L^p_e(\mathbb{R}^n)$ consist of all L^p-functions even in the x_n variable. If g is a function on $\mathbb{R}^{n-1} \times [0, \infty)$, we define $||g||^2_{1-n}$ by

$$\int_{\mathbb{R}^{n-1}} \int_0^\infty \left|\frac{\partial}{\partial t} g(u, t)\right|^2 t^{1-n} dt du.$$

Note that $|| \cdot ||_{1-n}$ is norm on $C^\infty_c(\mathbb{R}^{n-1} \times [0, \infty))$. Also, let $H^1_{1-n}(\mathbb{R}^{n-1} \times [0, \infty)) = \{g : ||g||_{1-n} < \infty\}/\sim$, where the equivalence relation $g \sim h$ is defined by $g(u, t) = h(u, t) + a(u)$ for some function $a(u)$. Then $H^1_{1-n}(\mathbb{R}^{n-1} \times [0, \infty))$ is a vector space and $|| \cdot ||_{1-n}$ becomes a norm on this space. Let $EC^\infty_c(\mathbb{R}^{n-1} \times [0, \infty))$ be defined as the quotient space $C^\infty(\mathbb{R}^{n-1} \times [0, \infty))/\sim$ and $[g] \in EC^\infty_c(\mathbb{R}^{n-1} \times [0, \infty))$ for $g \in C^\infty_c(\mathbb{R}^{n-1} \times [0, \infty))$ be the equivalence class of g.

Theorem 6. *$H^1_{1-n}(\mathbb{R}^{n-1} \times [0, \infty))$ is complete with respect to the norm $|| \cdot ||_{1-n}$ and has $EC^\infty_c(\mathbb{R}^{n-1} \times [0, \infty))$ as a dense subset.*

Proof. To show this space is complete with respect to $||\cdot||_{1-n}$, let $\{[g_i]\}_{i=1}^{\infty} \subset H^1_{1-n}(\mathbb{R}^{n-1} \times [0,\infty))$ be a Cauchy sequence. Then $\{\frac{\partial}{\partial t} g_i(u,t)\}_{i=1}^{\infty}$ is a Cauchy sequence in $L^2(\mathbb{R}^{n-1} \times [0,\infty), t^{1-n})$ with a measure $t^{1-n}dtdu$. Hence, there exists h in $L^2(\mathbb{R}^{n-1} \times [0,\infty), t^{1-n})$ such that

$$\int\limits_{\mathbb{R}^{n-1}} \int\limits_{0}^{\infty} \left| \frac{\partial}{\partial t} g_i(u,t) - h(u,t) \right|^2 t^{1-n} dtdu \to 0.$$

Define a function g by

$$g(u,t) := \int\limits_{0}^{t} h(u,r)dr.$$

Clearly, $\frac{\partial}{\partial t} g(u,t)$ is $h(u,t)$, $[g]$ is in $H^1_{1-n}(\mathbb{R}^{n-1} \times [0,\infty))$, and $||[g_i] - [g]||_{1-n}$ goes to zero. This proves the completeness of $H^1_{1-n}(\mathbb{R}^{n-1} \times [0,\infty))$.

To show that $EC_c^{\infty}(\mathbb{R}^{n-1} \times [0,\infty))$ is dense in $H^1_{1-n}(\mathbb{R}^{n-1} \times [0,\infty))$ with respect to $||\cdot||^2_{1-n}$, pick $[g] \in H^1_{1-n}(\mathbb{R}^{n-1} \times [0,\infty))$. Then $\frac{\partial}{\partial t} g(u,t)$ is in $L^2(\mathbb{R}^{n-1} \times [0,\infty), t^{1-n})$, so there exists a sequence $\{h_i\}_{i=1}^{\infty}$ in $C_c^{\infty}(\mathbb{R}^{n-1} \times [0,\infty))$ such that

$$\int\limits_{\mathbb{R}^{n-1}} \int\limits_{0}^{\infty} \left| h_i(u,t) - \frac{\partial}{\partial t} g(u,t) \right|^2 t^{1-n} dtdu \to 0.$$

For each i, let $g_i(u,t) = \int_0^t h_i(u,r)dr$. Then the sequence $\{g_i\}_{i=1}^{\infty} \in C_c^{\infty}(\mathbb{R}^{n-1} \times [0,\infty))$ satisfies $h_i(u,t) = \frac{\partial}{\partial t} g_i(u,t)$ and $||g_i - g||_{1-n}$ goes to zero. Hence, for the sequence $\{[g_i]\}_{i=1}^{\infty} \in EC_c^{\infty}(\mathbb{R}^{n-1} \times [0,\infty))$, $||[g_i] - [g]||_{1-n}$ goes to zero. ☐

We get a following estimate and range description. From now on, let the equivalent class $[g]$ be denoted by g.

Theorem 7. *For $f \in L^2_e(\mathbb{R}^n)$, $||f||_2$ is equal to $||R_E f||_{1-n}$, up to a constant multiple factor. Furthermore, R_E is an isomorphism between $L^2_e(\mathbb{R}^n)$ and $H^1_{1-n}(\mathbb{R}^{n-1} \times [0,\infty))$.*

Proof. Let $g = R_E f$. The Plancherel formula implies

$$\begin{aligned} \int\limits_{\mathbb{R}^{n-1}} \left| H_n \frac{1}{t^{n-1}} \frac{\partial}{\partial t} g(u,\cdot)(\rho) \right|^2 du &= \int\limits_{\mathbb{R}^{n-1}} \left| H_n \frac{1}{t^{n-1}} \frac{\partial}{\partial t} \hat{g}(\eta,\cdot)(\rho) \right|^2 d\eta \\ &= \lambda^{-1} \nu^{-n+2} \int\limits_{\mathbb{R}^{n-1}} \left| H_n \frac{1}{t^{n-1}} \frac{\partial}{\partial t} \hat{g}\left(\frac{\eta_1}{\lambda}, \frac{\tilde{\eta}}{\nu}, \cdot \right)(\rho) \right|^2 d\eta. \end{aligned} \tag{10}$$

Note that $f(x) = H_n H_n f(x)$ for a radial function f on $\mathbb{R}^n$. By the Plancherel formula, we get

$$\int_0^\infty |f(r)|^2 r^{n-1} dr = \int_0^\infty |H_n f(\rho)|^2 \rho^{n-1} d\rho. \tag{11}$$

Combining two above equations (10) and (11), we get

$$\begin{aligned}
||g||_{1-n}^2 &= \int_{\mathbb{R}^{n-1}} \int_0^\infty \left| \frac{\partial}{\partial t} g(u,t) \right|^2 t^{1-n} dt du = \int_{\mathbb{R}^{n-1}} \int_0^\infty \left| \frac{1}{t^{n-1}} \frac{\partial}{\partial t} g(u,t) \right|^2 t^{n-1} dt du \\
&= \int_{\mathbb{R}^{n-1}} \int_0^\infty \left| H_n \frac{1}{t^{n-1}} \frac{\partial}{\partial t} g(u,\cdot)(\rho) \right|^2 \rho^{n-1} d\rho du \\
&= \lambda^{-1} \nu^{-n+2} \int_{\mathbb{R}^{n-1}} \int_0^\infty \left| H_n \frac{1}{t^{n-1}} \frac{\partial}{\partial t} \hat{g} \left(\frac{\eta_1}{\lambda}, \frac{\tilde{\eta}}{\nu}, \cdot \right) (\rho) \right|^2 \rho^{n-1} d\rho d\eta \\
&= 2^{n/2+1} \pi^{n/2} \int_{\mathbb{R}^{n-1}} \int_{|\eta|}^\infty \frac{\rho}{\sqrt{\rho^2 - |\eta|^2}} \left| \hat{f} \left(\frac{\eta_1}{\lambda}, \frac{\tilde{\eta}}{\nu}, \frac{\sqrt{\rho^2 - |\eta|^2}}{\nu} \right) \right|^2 d\rho d\eta \\
&= 2^{n/2+1} \pi^{n/2} C(\lambda) \int_{\mathbb{R}^n} |\widehat{f}(\eta,\rho)|^2 d\eta d\rho.
\end{aligned}$$

In the fourth lines, we used equations (6) and (7), and in the last line, we changed to a variable $\rho_{new} = \sqrt{\rho^2 - |\eta|^2}/\nu$ and then variables $\eta_{1,new} = \eta_1/\lambda, \eta_{i,new} = \eta_i/\nu$ for $i = 2, \cdots, n-1$.

To show that R_E is an isomorphism, pick $g \in EC_c^\infty(\mathbb{R}^{n-1} \times [0,\infty))$. It is routine to check $R_E^*(1/t^{n-1} \frac{\partial}{\partial t} g) \in C_c^\infty(\mathbb{R}^n)$. $\hat{f} \in L_e^2(\mathbb{R}^n) \cap L_e^1(\mathbb{R}^n)$ follows from equation (8), so $f \in L_e^2(\mathbb{R}^n)$. Therefore, R_E is an isomorphism since $C_c^\infty(\mathbb{R}^n) \cap L_e^2(\mathbb{R}^n)$ and $EC_c^\infty(\mathbb{R}^{n-1} \times [0,\infty))$ are dense in $L_e^2(\mathbb{R}^n)$ and $H_{1-n}^1(\mathbb{R}^{n-1} \times [0,\infty))$ with respect to $|| \cdot ||_2$ and $|| \cdot ||_{1-n}$, respectively. □

6. Uniqueness for the Local Problem

Theorem 7 implies $f \in L_e^2(\mathbb{R}^n)$ is uniquely determined by $R_E f$. The question arises if f is uniquely determined by some partial information. The approach in this section is similar to the one in [3].

Theorem 8. *Let $u^0 \in \mathbb{R}^{n-1}$, $\epsilon > 0$, and $R > 0$ be arbitrary. Let $f \in L_e^2(\mathbb{R}^n)$ and suppose $g = R_E f$ is equal to zero on the open set*

$$U_{T,\epsilon} = \{(u,t) \in \mathbb{R}^{n-1} \times [0,\infty) : |u - u^0| < \epsilon, 0 \leq t < T\}.$$

Then f equals zero on the open set

$$V_T = \left\{ x \in \mathbb{R}^n : \frac{(x_1 - u_1^0)^2}{\lambda^2} + \frac{(\tilde{x} - \tilde{u}^0)^2}{\nu^2} + \frac{x_n^2}{\nu^2} < T^2 \right\}.$$

Here $x = (x_1, \tilde{x}, x_n) \in \mathbb{R}^n$ and $u^0 = (u_1^0, \tilde{u}^0) \in \mathbb{R}^{n-1}$. Also, g is equal to zero on the open cone

$$W_T = \{(u,t) \in \mathbb{R}^{n-1} \times [0,T) : |u - u_0| + t < T\}.$$

Proof. Without loss of generality, we may assume $u^0 = 0$. Let $f \in C^\infty(\mathbb{R}^n)$. Clearly, g is also differentiable. Differentiating $R_E f(u,t)$ with respect to u_i yields

$$\begin{aligned} \frac{\partial}{\partial u_i} R_E f(u,t) &= C(\lambda) \int\limits_{\mathbb{R}^n} \chi_{|x|<t} \frac{\partial}{\partial u_i} f(\lambda x_1 + u_1, \nu\tilde{x} + \tilde{u}, \nu x_n) dx \\ &= C(\lambda) \frac{1}{t} \int\limits_{|x|=t} x_i \frac{\partial}{\partial x_i} f(\lambda x_1 + u_1, \nu\tilde{x} + \tilde{u}, \nu x_n) dx. \end{aligned}$$

Here we used equation (1) and the divergence theorem. Using equation (2), we get

$$\begin{aligned} \frac{\partial}{\partial t} R_E(x_i f)(u,t) &= C(\lambda) \int\limits_{|x|=t} (\nu x_i + u_i) f(\lambda x_1 + u_1, \nu\tilde{x} + \tilde{u}, \nu x_n) d\sigma(x) \\ &= C(\lambda) \left(t\nu \frac{\partial}{\partial u_i} g(u,t) + u_i \frac{\partial}{\partial t} g(u,t) \right). \end{aligned}$$

Let the linear operator D_i be defined by the above expression. Then $\frac{\partial}{\partial t} R_E(x_i f)(u,t)$ is $D_i g(u,t)$. By iteration, we obtain $\frac{\partial}{\partial t} R_E(p(x')f) = p(D)g$ where p is an $n-1$-variable polynomial. If g is zero in $U_{T,\epsilon}$, then $p(D)g$ is also zero in $U_{T,\epsilon}$. Then we have for any point $(u,t) \in U_{T,\epsilon}$,

$$\begin{aligned} \frac{\partial}{\partial t} R_E(p(x')f)(u,t) &= C(\lambda) \int\limits_{|x|=t} p(\lambda x_1 + u_1, \nu\tilde{x} + \tilde{u}) f(\lambda x_1 + u_1, \nu\tilde{x} + \tilde{u}, \nu x_n) d\sigma(x) \\ &= C(\lambda) \int\limits_{|y|<t} p(u + (\lambda y_1, \nu\tilde{y})) f(u + (\lambda y_1, \nu\tilde{y}), \nu\sqrt{t^2 - |y|^2}) \frac{dy}{\sqrt{t^2 - |y|}} = 0. \end{aligned}$$

For fixed u and t, choose a sequence of polynomials such that $p_i(u + (\lambda y_1, \nu\tilde{y}))$ converge to $f(u + (\lambda y_1, \nu\tilde{y}, \nu\sqrt{t^2 - |y|^2}))$ uniformly for $|y| \leq t$ and $y = (y_1, \tilde{y}) \in \mathbb{R}^{n-1}$. It follows that $f = 0$ in V_T and that $g = 0$ in W_T.

To extend to the case $f \in L^2(\mathbb{R}^n)$, we choose a sequence of $g_i \in C^\infty(\mathbb{R}^n)$ such that $||g_i - g||_{1-n} \to 0$ where $g = R_E f$. We may assume $g_i = 0$ in $U_{T_i,\epsilon_i} \subset U_{T,\epsilon}$ such that $T_i \to T$ and $\epsilon_i \to \epsilon$. By theorem 7, there exist f_i such that $R_E f_i = g_i$ and f_i converge to f in the $L^2(\mathbb{R}^n)$ sense. Thus f_i is zero on V_{T_i}, so f is also zero on V_T. Then g also vanishes in W_T. ☐

Corollary 9. *If $g = 0$ in a strip $\{(u,t) \in \mathbb{R}^{n-1} \times [0,\infty) : |u - u_0| < \epsilon, 0 \leq t < \infty\}$ then f and g are zero everywhere.*

7. Conclusion

We describe two different ways of determining a function f from its n-dimensional elliptical Radon transform $R_E f$ arising in radio tomography imaging [16, 15, 17]. We also present a Sobolev stability estimate, range description and a local uniqueness result for R_E.

Acknowledgements

The author thanks P Kuchment and D Steinhauer for fruitful discussions. This work was supported in part by US NSF Grants DMS 0908208 and DMS 1211463.

References

[1] G. Ambartsoumian, R. Felea, V. P. Krishnan, C. Nolan, and E. T. Quinto. A class of singular Fourier integral operators in synthetic aperture radar imaging. *ArXiv e-prints*, October 2011.

[2] G. Ambartsoumian, V. P. Krishnan, and E. T. Quinto. Microlocal analysis of an ultrasound transform with circular source and receiver trajectories. *Contemporary Mathematics*, to appear.

[3] L. Andersson. On the determination of a function from spherical averages. *SIAM Journal on Mathematical Analysis*, 19(1):214–232, 1988.

[4] J.D. Coker and A.H. Tewfik. Multistatic sar image reconstruction based on an elliptical-geometry radon transform. In *Waveform Diversity and Design Conference, 2007. International*, pages 204 –208, june 2007.

[5] A. Erdelyi. *Tables of Integral Transforms, Vols. I and II.* Batemann Manuscript Project, McGrawHill,New York, 1954.

[6] J. Fawcett. Inversion of n-dimensional spherical averages. *SIAM Journal on Applied Mathematics*, 45(2):336–341, 1985.

[7] R. Gouia-Zarrad and G. Ambartsoumian. Approximate inversion algorithm of the elliptical radon transform. In *Mechatronics and its Applications (ISMA), 2012 8th International Symposium on*, pages 1 –4, april 2012.

[8] V. Krishnan and E. T. Quinto. Microlocal aspects of common offset synthetic aperture radar imaging. *Inverse Problems and Imaging*, 5:659–674, 2011.

[9] V. P. Krishnan, H. Levinson, and E. T. Quinto. Microlocal analysis of elliptical radon transforms with foci on a line. In Irene Sabadini and Daniele C Struppa, editors, *The Mathematical Legacy of Leon Ehrenpreis*, volume 16 of *Springer Proceedings in Mathematics*, pages 163–182. Springer Milan, 2012.

[10] P. Kuchment, K. Lancaster, and L. Mogilevskaya. On local tomography. *Inverse Problems*, 11(3), 1995.

[11] F. Natterer. *The Mathematics of Computerized Tomography.* Classics in Applied Mathematics. Society for Industrial and Applied Mathematics, 2001.

[12] F. Natterer and F. Wübbeling. *Mathematical methods in image reconstruction.* SIAM Monographs on mathematical modeling and computation. SIAM, Society of industrial and applied mathematics, Philadelphia (Pa.), 2001.

[13] S. Nilsson. *Application of Fast Backprojection Techniques for Some Inverse Problems of Integral Geometry.* Linköping studies in science and technology: Dissertations. Department of Mathematics, Linköping University, 1997.

[14] N. T. Redding and G. N. Newsam. Inverting the circular radon transform. *DTSO Research Report DTSO-Ru-0211*, August 2001.

[15] J. Wilson and N. Patwari. Through-Wall Tracking Using Variance-Based Radio Tomography Networks. *ArXiv e-prints*, 2009.

[16] J. Wilson and N. Patwari. Radio tomographic imaging with wireless networks. *Mobile Computing, IEEE Transactions on*, 9(5):621 –632, may 2010.

[17] J. Wilson, N. Patwari, and Vasquesz. Regularization Methods for Radio Tomographic Imaging. *Virginia Tech Symposium on Wireless Personal Communications*, 2009.